Tyrone Camarero Specifications

Camarero DS4007UX-110R4L1 **Key features**

- Qualified low latency NICs, World Record Performance, STAC® report, RedHat® OpenShift CollaborationFinancial Analysis, Business Critical Applications, Enterprise Server
- Dual socket P (LGA 3647) supports, Intel® Xeon® Scalable Processors, Dual UPI up to 10.4GT/s,(Intel® Xeon® Gold 6144 included)
- Intel® C621 chipset
- Up to 2TB ECC 3DS LRDIMM or RDIMM,up to DDR4-2666MHz; 16 DIMM slots, (12x 16GB DDR4-2666MHz included)
- 2 PCI-E 3.0 x16 slots (FH, 10.5"/10" L),1 PCI-E 3.0 x8 (LP), 1 PCI-E 3.0 x8,(internal SAS3 integrated 3108)
- 4 Gigabit Ethernet ports
- 8 Hot-swap 2.5" SAS3 drive Bays;2 Hot-swap NVMe bays
- 8 heavy duty fans w/ optimal, fan speed control
- 750W Redundant Power Supplies Platinum Level (94%+)









Processor/Cache

Dual socket P (LGA 3647) supports, Intel® Processor

Xeon® Scalable Processors, Dual UPI up

to 10.4GT/s,(Intel® Xeon® Gold

6144 included)

Chipset

Chipset Intel® C621 chipset

System Memory

Memory Capacity Up to 2TB ECC 3DS LRDIMM or RDIMM,

> up to DDR4-2666MHz; 16 DIMM slots, (12x 16GB DDR4-2666MHz included)

Expansion Slots

2 PCI-E 3.0 x16 slots (FH, 10.5"/10" L), **PCI-Express**

1 PCI-E 3.0 x8 (LP), 1 PCI-E 3.0 x8,

(internal SAS3 integrated 3108)

Integrated On-Board

Broadcom 3108 controller for 8 SAS

SAS3 ports

SATA3 (disabled) SATA

LAN 4 RJ45 Gigabit Ethernet ports,1 RJ45

Dedicated IPMI LAN port

Add-on Options

Optical Drive None

Front Panel

LED Indicators Power LED, Hard drive activity LED,

Network activity LEDs, System Overheat

LED / Fan fail LED / UID LED

Power On/Off button, System Reset button **Buttons**

Drive Bays

HDD bays 8 Hot-swap 2.5" SAS3 drive bays, 2 Hot-swap

2.5" NVMe

Power Supply

750W Redundant Power Supplies Platinum Level (94%+)

Cooling System

8 heavy duty fans w/ optimal, fan speed control

Form Factor

Form Factor 1U Rackmount 1.7" (43mm), Height 17.2" (437mm), Width 28.5" (724mm) Depth

Email: info@tyronesystems.com For more/current product information, visit www.tyronesystems.com